

Station	Time	Altitude	Latitude	Longitude	Remarks
1	0000	0	00° 00' 00"	00° 00' 00"	Start of observation
2	0005	10	00° 00' 00"	00° 00' 00"	First observation
3	0010	20	00° 00' 00"	00° 00' 00"	Second observation
4	0015	30	00° 00' 00"	00° 00' 00"	Third observation
5	0020	40	00° 00' 00"	00° 00' 00"	Fourth observation
6	0025	50	00° 00' 00"	00° 00' 00"	Fifth observation
7	0030	60	00° 00' 00"	00° 00' 00"	Sixth observation
8	0035	70	00° 00' 00"	00° 00' 00"	Seventh observation
9	0040	80	00° 00' 00"	00° 00' 00"	Eighth observation
10	0045	90	00° 00' 00"	00° 00' 00"	Ninth observation
11	0050	100	00° 00' 00"	00° 00' 00"	Tenth observation
12	0055	110	00° 00' 00"	00° 00' 00"	Eleventh observation
13	0100	120	00° 00' 00"	00° 00' 00"	Twelfth observation
14	0105	130	00° 00' 00"	00° 00' 00"	Thirteenth observation
15	0110	140	00° 00' 00"	00° 00' 00"	Fourteenth observation
16	0115	150	00° 00' 00"	00° 00' 00"	Fifteenth observation
17	0120	160	00° 00' 00"	00° 00' 00"	Sixteenth observation
18	0125	170	00° 00' 00"	00° 00' 00"	Seventeenth observation
19	0130	180	00° 00' 00"	00° 00' 00"	Eighteenth observation
20	0135	190	00° 00' 00"	00° 00' 00"	Nineteenth observation
21	0140	200	00° 00' 00"	00° 00' 00"	Twentieth observation
22	0145	210	00° 00' 00"	00° 00' 00"	Twenty-first observation
23	0150	220	00° 00' 00"	00° 00' 00"	Twenty-second observation
24	0155	230	00° 00' 00"	00° 00' 00"	Twenty-third observation
25	0200	240	00° 00' 00"	00° 00' 00"	Twenty-fourth observation
26	0205	250	00° 00' 00"	00° 00' 00"	Twenty-fifth observation
27	0210	260	00° 00' 00"	00° 00' 00"	Twenty-sixth observation
28	0215	270	00° 00' 00"	00° 00' 00"	Twenty-seventh observation
29	0220	280	00° 00' 00"	00° 00' 00"	Twenty-eighth observation
30	0225	290	00° 00' 00"	00° 00' 00"	Twenty-ninth observation
31	0230	300	00° 00' 00"	00° 00' 00"	Thirtieth observation
32	0235	310	00° 00' 00"	00° 00' 00"	Thirty-first observation
33	0240	320	00° 00' 00"	00° 00' 00"	Thirty-second observation
34	0245	330	00° 00' 00"	00° 00' 00"	Thirty-third observation
35	0250	340	00° 00' 00"	00° 00' 00"	Thirty-fourth observation
36	0255	350	00° 00' 00"	00° 00' 00"	Thirty-fifth observation
37	0300	360	00° 00' 00"	00° 00' 00"	Thirty-sixth observation
38	0305	370	00° 00' 00"	00° 00' 00"	Thirty-seventh observation
39	0310	380	00° 00' 00"	00° 00' 00"	Thirty-eighth observation
40	0315	390	00° 00' 00"	00° 00' 00"	Thirty-ninth observation
41	0320	400	00° 00' 00"	00° 00' 00"	Fortieth observation
42	0325	410	00° 00' 00"	00° 00' 00"	Forty-first observation
43	0330	420	00° 00' 00"	00° 00' 00"	Forty-second observation
44	0335	430	00° 00' 00"	00° 00' 00"	Forty-third observation
45	0340	440	00° 00' 00"	00° 00' 00"	Forty-fourth observation
46	0345	450	00° 00' 00"	00° 00' 00"	Forty-fifth observation
47	0350	460	00° 00' 00"	00° 00' 00"	Forty-sixth observation
48	0355	470	00° 00' 00"	00° 00' 00"	Forty-seventh observation
49	0400	480	00° 00' 00"	00° 00' 00"	Forty-eighth observation
50	0405	490	00° 00' 00"	00° 00' 00"	Forty-ninth observation
51	0410	500	00° 00' 00"	00° 00' 00"	Fiftieth observation
52	0415	510	00° 00' 00"	00° 00' 00"	Fifty-first observation
53	0420	520	00° 00' 00"	00° 00' 00"	Fifty-second observation
54	0425	530	00° 00' 00"	00°	

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT I, Takayuki Shimizu, a citizen of Japan residing at Kawasaki, Japan have invented certain new and useful improvements in

LOW-COST WDM TERMINAL DEVICE ACCOMMODATING PLURALITY OF CLIENT SIGNAL

of which the following is a specification : -

TITLE OF THE INVENTION

LOW-COST WDM TERMINAL DEVICE ACCOMMODATING
PLURALITY OF CLIENT SIGNAL

5 BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a WDM
(Wavelength Division Multiplex) terminal device and
a WDM network. More particularly, the present
10 invention relates to a WDM terminal device
accommodating a client signal in a WDM network, and
the WDM network.

2. Description of the Related Art

According to a related art, accommodation
15 of a client signal to a WDM system is performed
separately for each wave, by use of an optical fiber
corresponding to the wave. All the client signals
are initially converted from a light-signal format
to an electric-signal format, and, then, converted
20 from the electric-signal format to a light-signal
format, by a transponder, inside or near the WDM
system. Subsequently, all the client signals are
accommodated in the WDM system. The above-described
steps are performed because a wavelength of each
25 client signal supplied to the WDM system is
different from a wavelength of each client signal
inside the WDM system.

Two types of methods are taken for
accommodating a plurality of client signals located
30 at a distant place, according to the related art.
According to a first method shown in FIG. 1, client
signals to be accommodated in a WDM system are
transmitted separately by use of optical fibers
whose number is equal to the number of the client
35 signals, from the distant place to the WDM system.
Subsequently, the client signals are accommodated in
WDM terminal devices 10 or 11, or a WDM-ADM (Add-

Drop Multiplexer) device 12 of the WDM system, through a transponder.

On the other hand, according to a second method shown in FIG. 2, a WDM terminal device 15 of a small-capacity WDM system initially carries out wavelength multiplexing to client signals at a distant place. Subsequently, the WDM terminal device 15 transmits the client signals closer to a WDM system that accommodates the client signals at the end. Next, a WDM terminal device 16 of the small WDM system separates the client signals by each wave. Finally, the client signals are accommodated in the WDM terminal devices 10 or 11, or the WDM-ADM device 12 of the WDM system.

For example, a wavelength-multiplexed signal having tens of channels is transmitted or received between the WDM terminal devices 10 or 11, and the WDM-ADM device 12 at a 0.4nm interval through a band whose wavelength is 1500nm. On the other hand, a wavelength-multiplexed signal having several to ten odd channels is transmitted or received between the WDM terminal devices 15 and 16, at a 1.6nm interval through a band whose wavelength is 1500nm, for instance.

Additionally, in the related art, system setting and management are independently performed to each of a long-distance WDM system, a middle or short distance WDM system and a MUX (Multiplexer) of a SONET (Synchronous Optical Network) system by use of its own EMS (Element Management System) and data link. Therefore, in a case in which a client constructs a network by combining each system, complicated management of the entire network by use of a plurality of EMSs is necessary.

Additionally, according to the first method, optical fibers whose number is equal to the number of the client signals to be accommodated are

necessarily placed or leased between the distant place and the WDM system. Thus, a cost of achieving the first method is high.

Further, according to the second method,
5 the WDM terminal devices 15 and 16 of the small-capacity WDM system are necessarily placed at two positions right before the distant place and the WDM system accommodating the client signals at the end. Consequently, a cost of achieving the second method
10 is also high.

SUMMARY OF THE INVENTION

Accordingly, it is a general object of the present invention to provide a WDM (Wavelength
15 Division Multiplexed) terminal device and a WDM network. A more particular object of the present invention is to provide a WDM terminal device and a WDM network that can accommodate a plurality of client signals from a distant place at low cost.

20 The above-described object of the present invention is achieved by a WDM terminal device located in a WDM network, through which a plurality of client signals are transmitted with their wavelengths being multiplexed, the WDM terminal
25 device including a first compensator that collectively compensates dispersion of each wavelength of a first plurality of client signals received through the WDM network with their wavelengths being multiplexed; a transmission
30 amplifier that collectively adjusts levels of the first plurality of client signals; and a multiplexing unit that multiplexes a wavelength of a client signal having a single wavelength or a wavelength of at least one of a second plurality of
35 client signals whose wavelengths are multiplexed, to wavelengths of the first plurality of client signals, and transmits the first plurality of client signals.

Thus, the WDM terminal device can multiplex wavelengths of a plurality of client signals received from a metro WDM terminal device located at a distant place, to a wavelength of another client signal without separating the plurality of client signals by each wavelength, thereby achieving accommodation of a plurality of client signals whose wavelengths are multiplexed, at low cost.

Another object of the present invention is to provide a WDM network, in which a single EMS (Element Management System) can carry out system setting and management of all WDM terminal devices, WDM-ADM (Add-Drop Multiplexer) devices, and SONET (Synchronous Optical Network) devices connected to the WDM devices, in the WDM network.

The above-described object of the present invention is achieved by a WDM network, through which a plurality of client signals are transmitted with their wavelengths being multiplexed, the WDM network comprising a provisioning unit that is connected to a WDM terminal device, and carries out provisioning to all WDM terminal devices, WDM-ADM devices, and SONET devices connected to the WDM devices, in the WDM network.

Other objects, features and advantages of the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings.

30

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a diagram showing a system structure of a related-art WDM system;

FIG. 2 is a diagram showing a system structure of another related-art WDM system;

FIG. 3 is a diagram showing a system structure of a WDM system according to an embodiment

of the present invention;

FIG. 4 is a block diagram showing a structure of a long-haul WDM terminal device;

FIG. 5 is a block diagram showing a structure of a WDM-ADM device; and

FIG. 6 is a block diagram showing a structure of a metro WDM terminal device.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

10 A description will now be given of preferred embodiments of the present invention, with reference to the accompanying drawings.

FIG. 3 shows a system structure of a WDM system according to an embodiment of the present invention. As shown in FIG. 3, a long-haul WDM system includes long-haul WDM terminal devices 20 and 21, a WDM-ADM device 22 and an optical fiber. The optical fiber connects the long-haul WDM terminal devices 20 and 21, with the WDM-ADM device 22. A client signal from a router 24 is transmitted through an optical fiber, and is accommodated through a transponder in the long-haul WDM terminal devices 20 or 21.

At a distant place, a client signal from routers 26 and 27 is transmitted through an optical fiber, and is accommodated through a transponder in a metro WDM terminal device 28 that composes a metro WDM system. Additionally, a client signal from a router 30 is transmitted through an optical fiber, and is multiplexed by a MUX (SONET-MUX) 32 of a SONET system. Subsequently, the multiplexed client signal is accommodated through a transponder in the metro WDM terminal device 28.

The metro WDM terminal device 28 carries out wavelength multiplexing to the accommodated client signal, and transmits the multiplexed client signal to the long-haul WDM terminal devices 20 and

21, and the WDM-ADM device 22. Subsequently, the long-haul WDM terminal devices 20 and 21, and the WDM-ADM device 22 accommodate the multiplexed client signal.

5 The metro WDM terminal device 28 transmits or receives a wavelength-multiplexed signal having several to ten odd channels through a band whose wavelength is 1500nm, at a 0.4nm interval. The long-haul WDM terminal devices 20 and 21, and the
10 WDM-ADM device 22 transmit or receive a wavelength-multiplexed signal having tens of channels through a band whose wavelength is 1500nm, at a 0.4nm interval. Any client signals are transmitted between the metro WDM system and the long-haul WDM system at a same
15 wavelength. In other words, a light signal whose wavelength is multiplexed by the metro WDM terminal device 28 is accommodated in the long-haul WDM system without going through a transponder, or without being converted from a light-signal format
20 through an electric-signal format to another light-signal format.

 Additionally, the long-haul WDM terminal device 20 is connected with a common EMS terminal device 34. The common EMS terminal device 34
25 carries out network setting and manages the long-haul WDM terminal devices 20 and 21, the WDM-ADM device 22, the metro WDM terminal device 28 and the SONET-MUX 32, collectively. It should be noted that the common EMS terminal device 34 could be connected
30 to the long-haul WDM terminal device 21 or the WDM-ADM device 22 instead of the long-haul WDM terminal device 20.

 FIG. 4 is a block diagram showing a structure of the long-haul WDM terminal devices 20
35 and 21. In FIG. 4, a client-signal flow and a control-signal flow are indicated as a solid line and a broken line, respectively.

As shown in FIG. 4, a plurality of client signals (WDM client signals) whose wavelengths are multiplexed and are transmitted from a distant place by the metro WDM system are supplied to a WDM collective transmission amplifier (a transmission amp) 42. A plural-wavelengths collective dispersion compensator (a compensator) 40 provided next to the WDM collective transmission amplifier 42 compensates dispersion accumulated by the metro WDM transmission to a level suitable for the next long-haul WDM transmission. The WDM collective transmission amplifier 42 adjusts the WDM client signals processed through dispersion compensation to an output level appropriate as an input to a wavelength-multiplexing unit (a multiplexing unit) 44.

An amplifier control unit (an amp control unit) 50 controls the output level of the WDM collective transmission amplifier 42, based on a result of monitoring an output of a WDM collective transmission amplifier (a transmission amp) 46 by using a spectrum analyzer 48. Similarly, an amplifier control unit (an amp control unit) 51 controls an output level of the WDM collective transmission amplifier 46, based on the monitoring result of the spectrum analyzer 48.

The WDM client signals whose output levels are adjusted by the WDM collective transmission amplifier 42 are inputted to the wavelength-multiplexing unit 44. Subsequently, the wavelength-multiplexing unit 44 multiplexes wavelengths of the WDM client signals supplied from the WDM collective transmission amplifier 42, with other WDM client signals or client signals accommodated separately for each wave through transponders 58. The WDM client signals are, then, processed through level adjustment at the WDM collective transmission

amplifier 46, and dispersion compensation at a plural-wavelengths collective dispersion compensator (a compensator) 45 for securing the next WDM transmission performance. Subsequently, the WDM client signals are transmitted to a long-haul WDM network.

On the other hand, a WDM signal transmitted through the long-haul WDM network is supplied to a WDM collective reception amplifier (a reception amp) 54. A plural-wavelengths collective dispersion compensator (a compensator) 52 compensates dispersion of the WDM signal accumulated by the long-haul WDM transmission. Additionally, the WDM collective reception amplifier 54 adjusts a level of the WDM signal. Subsequently, a variable-separation-wavelength-separating unit (a separating unit) 56 separates the WDM signal.

The variable-separation-wavelength-separating unit 56 can freely separate the WDM signal into one or a plurality of wavelength-multiplexed signals, according to setting. A signal separated by a single wave is transmitted through the transponder 58 to a client side (via a router).

A plurality of WDM signals to be transmitted to a distant place with their wavelengths being multiplexed are separated by the variable-separation-wavelength-separating unit 56. Subsequently, a WDM collective transmission amplifier (a transmission amp) 62 amplifies the WDM signals to a level appropriate for the next metro WDM transmission. Additionally, a plural-wavelength collective dispersion compensator (a compensator) 60 carries out dispersion compensation to the WDM signals, in order to insure the next WDM transmission performance. The WDM signals are, then, transmitted to a metro WDM network.

An amplifier control unit (an amp control

unit) 55 controls an output level of the WDM collective reception amplifier 54, based on a result of monitoring an output of the WDM collective reception amplifier 54 by using a spectrum analyzer 53. Additionally, an amplifier control unit (an amp control unit) 64 controls an output level of the WDM collective transmission amplifier 62, based on a result of monitoring an output of the WDM collective transmission amplifier 62 by using a spectrum analyzer 63.

FIG. 5 is a block diagram showing a structure of the WDM-ADM device 22. A plurality of client signals (WDM client signals) whose wavelengths are multiplexed and are transmitted by the metro WDM system from a distant place are supplied to a WDM collective transmission amplifier (a transmission amp) 142. A plural-wavelengths collective dispersion compensator (a compensator) 140 provided next to the WDM collective transmission amplifier 142 compensates dispersion accumulated by the metro WDM transmission to a level appropriate for the next long-haul WDM transmission.

The WDM collective transmission amplifier 142 adjusts the WDM client signals processed through dispersion compensation to an output level appropriate as an input to a variable-separation-wavelength add/drop unit (an add/drop unit) 144. An amplifier control unit (an amp control unit) 143 controls the output level of the WDM collective transmission amplifier 142, based on a result of monitoring an output of the WDM collective transmission amplifier 142 by using a spectrum analyzer 141.

The variable-separation-wavelength add/drop unit 144 adds (carries out wavelength multiplexing) the WDM client signals whose output levels have been adjusted, to a wavelength of a

signal that passes through the WDM-ADM device 22 and is supplied from the long-haul WDM terminal device 20 through a WDM collective reception amplifier (a reception amplifier) 120, with other WDM client
5 signals or client signals accommodated for each wave.

A plural-wavelengths collective dispersion compensator (a compensator) 146 and a WDM collective transmission amplifier (a transmission amp) 148 carry out dispersion compensation and appropriate
10 level adjustment, respectively, to a group of signals obtained by the above-described addition, for securing the next WDM transmission performance. Subsequently, the group of signals is transmitted to the long-haul WDM network. An amplifier control
15 unit (an amp control unit) 150 controls an output level of the WDM collective transmission amplifier 148, based on a result of monitoring an output of the WDM collective transmission amplifier 148 by using a spectrum analyzer 149.

20 On the other hand, a plural-wavelengths collective dispersion compensator (a compensator) 152 compensates dispersion of a WDM signal transmitted from the long-haul WDM terminal device 21 through the long-haul WDM network, in which the
25 dispersion is accumulated by the long-haul WDM transmission. Additionally, a WDM collective reception amplifier (a reception amp) 154 adjusts a level of the WDM signal. Subsequently, the WDM signal is supplied to a variable-separation-
30 wavelength add/drop unit (an add/drop unit) 156, where a wavelength to be dropped at an own node (the WDM-ADM device 22) is separated.

The variable-separation-wavelength add/drop unit 156 can freely set a signal to be
35 separated from the WDM signal, to one or a plurality of wavelengths. A signal separated by a single wave is transmitted to a client side through a

transponder 158.

A plurality of wavelength-multiplexed signals to be transmitted to a distant place, after being separated from the WDM signal, are amplified
5 by a WDM collective transmission amplifier (a transmission amp) 162 to a level appropriate for the next metro WDM transmission. Subsequently, a plural-wavelengths collective dispersion compensator (a compensator) 160 compensates dispersion of the
10 plurality of wavelength-multiplexed signals, for securing the next WDM transmission performance. The plurality of wavelength-multiplexed signals are, then, transmitted to the metro WDM network.

An amplifier control unit (an amp control
15 unit) 155 controls an output level of the WDM collective reception amplifier 154, based on a result of monitoring an output of the WDM collective reception amplifier 154 by using a spectrum analyzer 153. Additionally, an amplifier control unit (an
20 amp control unit) 164 controls an output level of the WDM collective transmission amplifier 162, based on a result of monitoring an output of the WDM collective transmission amplifier 162 by using a spectrum analyzer 163.

FIG. 6 is a block diagram showing a
25 structure of the metro WDM terminal device 28. A client signal transmitted by each wave from a router is supplied to a wavelength-multiplexing unit (a multiplexing unit) 244 through a transponder 200. A
30 client signal transmitted by each wave from the SONET-MUX 32 is supplied to the wavelength-multiplexing unit 244 through a transponder 210. The wavelength-multiplexing unit 244 multiplexes wavelengths of the above client signals supplied
35 from the router and the SONET-MUX 32. Subsequently, a WDM collective transmission amplifier (a transmission amp) 246 adjusts a level of a WDM

signal obtained by multiplexing the wavelengths of the above client signals. Additionally, a plural-wavelengths collective dispersion compensator 245 (a compensator) compensates dispersion of the WDM
5 signal for securing the next WDM transmission performance. The WDM signal is, then, transmitted to the long-haul WDM network.

An output level of the WDM collective transmission amplifier 246 is controlled by an
10 amplifier control unit (an amp control unit) 250, based on a result of monitoring an output of the WDM collective transmission amplifier 246 by using a spectrum analyzer 248.

On the other hand, a WDM signal
15 transmitted through the metro WDM network is supplied to a WDM collective reception amplifier (a reception amp) 254. Subsequently, a plural-wavelengths collective dispersion compensator (a compensator) 252 compensates dispersion of the WDM
20 signal accumulated by the metro WDM transmission. Additionally, the WDM collective reception amplifier 254 adjusts a level of the WDM signal. The WDM signal whose dispersion is compensated and level is adjusted is, then, separated by a wavelength-
25 separating unit (a separating unit) 256. An output level of the WDM collective reception amplifier 254 is controlled by an amplifier control unit (an amp control unit) 255, based on a result of monitoring an output of the WDM collective reception amplifier
30 254 by using a spectrum analyzer 253.

The wavelength-separating unit 256 separates the WDM signal by each wavelength, and outputs a separated signal through the transponder 200 to a client side (via the router), and through
35 the transponder 210 to the SONET-MUX 32.

A description will now be given of collective network setting and management performed

by the common EMS terminal device 34.

As shown in FIG. 4, each of the long-haul WDM terminal devices 20 and 21 further includes a long-haul WDM OSC-DCC (Optical Supervising Channel - Data Communication Channel) terminal unit (a long-haul OSC-DCC) 80, a metro WDM OSC-DCC terminal unit (a metro OSC-DCC) 82, an EMS interface terminal unit (an EMS interface) 84, a SONET-DCC terminal unit (a SONET-DCC) 86, a message processing/converting unit (a message unit) 88 and a device control unit 89. Additionally, the common EMS terminal device (a common EMS) 34 is connected to the EMS interface terminal unit 84.

The WDM-ADM device 22 shown in FIG. 5 includes a long-haul WDM OSC-DCC terminal unit (a long-haul OSC-DCC) 180, a metro WDM OSC-DCC terminal unit (a metro OSC-DCC) 182, an EMS interface terminal unit (an EMS interface) 184, a SONET-DCC terminal unit (a SONET-DCC) 186, a message processing/converting unit (a message unit) 188 and a device control unit 189. Additionally, the common EMS terminal device 34 is connected to the EMS interface terminal unit 184.

Additionally, the metro WDM terminal device 28 includes a metro WDM OSC-DCC terminal unit (a metro OSC-DCC) 282, an EMS interface terminal unit (an EMS interface) 284, a SONET-DCC terminal unit (a SONET-DCC) 286, a message processing/converting unit (a message unit) 288 and a device control unit 289. Additionally, the common EMS terminal device (a common EMS) 34 is connected to the EMS interface terminal unit 284.

In a case in which the common EMS terminal device 34 shown in FIG. 4 transmits a message written in a language such as a TL1 (Transactional Language 1) to the long-haul WDM terminal device 20 or 21, the message including provisioning

information about the long-haul WDM terminal device 20 or 21, the message processing/converting unit 88 of the long-haul WDM terminal device 20 or 21 receives the message through the EMS interface terminal unit 84, and recognizes that a destination of the message is the device 20 or 21. The message processing/converting unit 88, then, converts a format of the message to a format in which a long-haul WDM terminal device can recognize the message. Subsequently, the device control unit 89 carries out setting and management of each unit included in the long-haul WDM terminal device 20 or 21, based on the message whose format is converted. Accordingly, the long-haul WDM terminal device 20 or 21 can set output wavelengths of a plurality of transponders, output levels of a plurality of WDM collective transmission amplifiers and the like.

In a case in which the common EMS terminal device 34 shown in FIG. 4 transmits a message written in a language such as the TL1 to the long-haul WDM terminal device 20 or 21, the message including provisioning information about the metro WDM terminal device 28 connected to the long-haul WDM terminal device 20 or 21, the message processing/converting unit 88 of the long-haul WDM terminal device 20 or 21 receives the message through the EMS interface terminal unit 84. Subsequently, the message processing/converting unit 88 recognizes that the message must be transmitted to the metro WDM terminal device 28, and the metro WDM terminal device 28 that is a destination of the message and is accommodated by the long-haul WDM terminal device 20 or 21. The message processing/converting unit 88, then, converts a format of the message so that the metro WDM terminal device 28 can recognize the message.

The metro WDM OSC-DCC terminal unit 82

generates an optical supervising channel and a data communication channel (OSC-DCC) for setting and management of the metro WDM terminal device 28, based on the converted message. This OSC-DCC is

5 combined with other data as an OSC having a single wavelength, by an OSC generating unit (an OSC generator) 90. Subsequently, the OSC is combined with a main signal by a coupler 91, and transmitted as a WDM signal to the metro WDM terminal device 28.

10 A decoupler 292 of the metro WDM terminal device 28 separates the OSC for long-haul WDM transmission, from the WDM signal. Additionally, an OSC terminal unit (an OSC terminal) 293 separates the OSC-DCC from the OSC. The separated OSC-DCC is

15 supplied to the message processing/converting unit 288 through the metro WDM OSC-DCC terminal unit 282. The message processing/converting unit 288 recognizes that the destination of the message is the metro WDM terminal device 28, and converts the

20 format of the message so that the metro WDM terminal device 28 can recognize the message. Subsequently, the device control unit 289 carries out setting and management of each unit included in the metro WDM terminal device 28, based on the converted message.

25 In a case in which setting and management of the SONET-MUX 32 accommodated in the metro WDM terminal device 28 is performed, the message processing/converting unit 288 recognizes the OSC-DCC separated by the OSC terminal device 293 as a

30 message that must be transmitted to the SONET-MUX 32, and, thus, converts a format of the message so that the SONET-MUX 32 recognizes the message.

The SONET-DCC terminal unit 286 generates an OSC-DCC for setting and managing the SONET-MUX 32,

35 based on the converted message, and transmits the OSC-DCC to the SONET-MUX 32 through the transponder 210. Consequently, setting and management of the

SONET-MUX 32 are performed, in accordance with the OSC-DCC.

Accordingly, the above-described steps achieve setting of output wavelengths of a plurality of transponders and output levels of a plurality of WDM collective transmission amplifiers included in the metro WDM terminal device 28 and the SONET-MUX 32.

In a case in which the common EMS terminal device 34 shown in FIG. 4 transmits a message written in a language such as the TL1 to the long-haul WDM terminal device 20 or 21, the message including provisioning information about the metro WDM terminal device 28 accommodated in the WDM-ADM device 22 carrying out the long-haul WDM transmission, the message processing/converting unit 88 of the long-haul WDM terminal device 20 or 21 receives the message through the EMS interface terminal unit 84. Subsequently, the message processing/converting unit 88 recognizes that a destination of the message is the metro WDM terminal device 28, and the metro WDM terminal device 28 as the destination of the message. Since the metro WDM terminal device 28 is accommodated in the WDM-ADM device 22, the message processing/converting unit 88 converts a format of the message so that the WDM-ADM device 22 can recognize the message.

The long-haul WDM OSC-DCC terminal unit 80 generates an OSC-DCC for long-haul WDM transmission, based on the message whose format is converted. The OSC-DCC for the long-haul WDM transmission is combined with other data as an OSC having a single wavelength, by the OSC generating unit 90. Subsequently, the OSC is combined with a main signal by the coupler 91, and is transmitted as a WDM signal to the WDM-ADM device 22.

A decoupler 192 of the WDM-ADM device 22

shown in FIG. 5 separates the OSC for the long-haul WDM transmission from the WDM signal. Additionally, an OSC terminal unit 193 separates the OSC-DCC from the OSC. This OSC-DCC is, then, supplied to the message processing/converting unit 188 through the long-haul WDM OSC-DCC terminal unit 180. The message processing/converting unit 188 recognizes that the message is to be transmitted to a metro WDM terminal device, and the destination of the message is the metro WDM terminal device 28 accommodated in the WDM-ADM device 22. Thus, the message processing/converting unit 188 converts the format of the message so that the metro WDM terminal device 28 can recognize the message.

The metro WDM OSC-DCC terminal unit 182 generates an OSC-DCC for a metro WDM terminal device, based on the message whose format is converted. This OSC-DCC for a metro WDM terminal device is combined with other data as an OSC having a single wavelength, by an OSC generating unit (an OSC generator) 194. Additionally, the OSC is combined with a main signal as a WDM signal by a coupler 195, and is transmitted to the metro WDM terminal device 28.

The decoupler 292 of the metro WDM terminal device 28 shown in FIG. 6 separates the OSC for the long-haul WDM transmission from the WDM signal. Additionally, the OSC terminal unit 293 separates the OSC-DCC from the OSC. The separated OSC-DCC is supplied to the message processing/converting unit 288 through the metro WDM OSC-DCC terminal unit 282. The message processing/converting unit 288 recognizes that the message is to be transmitted to the metro WDM terminal device 28, and converts the format of the message so that the metro WDM terminal device 28 can recognize the message. Subsequently, the device

control unit 289 carries out setting and management of each unit included in the metro WDM terminal device 28, based on the message whose format is converted.

5 Accordingly, the above-described steps achieve setting of the output wavelengths of a plurality of transponders and the output levels of a plurality of WDM collective transmission amplifiers included in the metro WDM terminal device 28 and the
10 SONET-MUX 32 accommodated in the metro WDM terminal device 28.

 Now, a transmission path using a specific wavelength is provided between the routers 26 and 27, as shown in FIG. 3, a route of the transmission path
15 starting from the router 26 through the metro WDM terminal device accommodated in the long-haul WDM terminal device 20, the long-haul WDM terminal device 20, the WDM-ADM device 22 and the metro WDM terminal device 28 accommodated in the WDM-ADM
20 device 22, to the router 27.

 The long-haul WDM terminal device 20 constantly monitors a WDM signal received from the WDM-ADM device 22. In a case in which the long-haul WDM terminal device 20 detects a failure to the
25 specific wavelength such as a decrease in a reception level of the WDM signal, the long-haul WDM terminal device 20 searches through a wavelength management table stored in the common EMS terminal device 34, for a wavelength usable through all the
30 sections of the route between the routers 26 and 27. Subsequently, the long-haul WDM terminal device 20 assigns the wavelength as a new specific wavelength (a newly assigned wavelength) used for the transmission path.

35 The long-haul WDM terminal device 20 notifies the metro WDM terminal device 28 accommodating the router 26 about the newly assigned

wavelength, by using the metro WDM OSC-DCC terminal unit 82 shown in FIG. 4, and notifies the WDM-ADM device 22 about the newly assigned wavelength, by using the long-haul WDM OSC-DCC terminal unit 80.

5 Additionally, the long-haul WDM terminal device 20 notifies the metro WDM terminal device 28 accommodating the router 27 about the newly assigned wavelength, by using the long-haul WDM OSC-DCC terminal unit 80 and a DCC for the metro WDM

10 transmission, the DCC being converted by the WDM-ADM device 22.

The metro WDM terminal device 28 accommodating the router 27 changes output wavelengths of the transponders inside the metro WDM

15 terminal device 28 to the newly assigned wavelength. The WDM-ADM device 22 for the long-haul WDM transmission changes a setting of the variable-separation-wavelength add/drop units 144 and 156 shown in FIG. 5, to accommodate the newly assigned

20 wavelength. The long-haul WDM terminal device 20 changes a setting of the variable-separation-wavelength-separating unit 56 shown in FIG. 4, to output the newly assigned wavelength to the metro WDM terminal device 28 accommodating the router 26.

25 The metro WDM terminal device 28 accommodating the router 26 receives the newly assigned wavelength as a signal to be transmitted to the router 26.

As described above, the long-haul WDM terminal device 20 can assign a new wavelength in

30 the case in which the long-haul WDM terminal device 20 detects a failure to the specific wavelength such as a decrease in the reception level of the WDM signal.

Similarly, the WDM-ADM device 22 may

35 constantly monitor a WDM signal received from the long-haul WDM terminal device 20. In a case in which the WDM-ADM device 22 detects a failure to the

specific wavelength of the route such as a decrease in a reception level of the WDM signal, the WDM-ADM device 22 searches through the wavelength management table stored in the common EMS terminal device 34, for a wavelength usable through all the sections of the route between the routers 26 and 27.

Subsequently, the WDM-ADM device 22 assigns the wavelength as a new specific wavelength (a newly assigned wavelength) used for the transmission path.

The WDM-ADM device 22 notifies the metro WDM terminal device 28 accommodating the router 27 about the newly assigned wavelength, by using the metro WDM OSC-DCC terminal unit 182 shown in FIG. 5, and notifies the long-haul WDM terminal device 20 about the newly assigned wavelength, by using the long-haul WDM OSC-DCC terminal unit 180.

Additionally, the WDM-ADM device 22 notifies the metro WDM terminal device 28 accommodating the router 26 about the newly assigned wavelength, by using the long-haul WDM OSC-DCC terminal unit 180 and a DCC for the metro WDM transmission, the DCC being converted by the long-haul WDM terminal device 20.

The metro WDM terminal device 28 accommodating the router 27 changes the output wavelengths of the transponders inside the metro WDM terminal device 28 to the newly assigned wavelength. The WDM-ADM device 22 for the long-haul WDM transmission changes the setting of the variable-separation-wavelength add/drop unit 156 shown in FIG. 5, to drop the newly assigned wavelength. The metro WDM terminal device 28 accommodating the router 27 receives the newly assigned wavelength as a signal to be transmitted to the router 27.

As described above, the WDM-ADM device 22 can assign a new wavelength in the case in which the WDM-ADM device 22 detects a failure to the specific

wavelength such as a decrease in the reception level of the WDM signal.

Next, it is assumed in the long-haul WDM terminal device 20 shown in FIG. 4 that an alarm message generated at the metro WDM terminal device 28 is transmitted to the message processing/converting unit 88 through the metro WDM OSC-DCC terminal unit 82 by use of an OSC-DCC for metro WDM transmission. The message processing/converting unit 88 recognizes the alarm message as a message that should be outputted to the common EMS terminal device 34, and the metro WDM terminal device 28 as an origin of the alarm message. It is assumed that the metro WDM terminal device 28 is accommodated in the long-haul WDM terminal device 20. Additionally, the message processing/converting unit 88 converts a format of the alarm message to a format recognizable by the common EMS terminal device 34. The alarm message whose format has been converted is transmitted with other messages to the common EMS terminal device 34 through the EMS interface terminal unit 84.

Next, it is assumed that an alarm message generated at the metro WDM terminal device 28 is transmitted to the WDM-ADM device 22 shown in FIG. 5 by use of the OSC-DCC for the metro WDM transmission. In this case, the alarm message is transmitted to the message processing/converting unit 188 through the metro WDM OSC-DCC terminal unit 182. The message processing/converting unit 188 recognizes the alarm message as a message that should be transmitted to the common EMS terminal device 34 connected to the long-haul WDM terminal device 20, and the metro WDM terminal device 28 as an origin of the alarm message. It is assumed that the metro WDM terminal device 28 is accommodated in the WDM-ADM device 22. Additionally, the message

processing/converting unit 188 converts a format of the alarm message to a format recognizable by the long-haul WDM terminal device 20.

The long-haul WDM OSC-DCC terminal unit
5 180 generates an OSC-DCC for the long-haul WDM transmission, based on the alarm message whose format has been converted. This OSC-DCC for the long-haul WDM transmission is, then, combined with other data as an OSC having a single wavelength, by
10 the OSC generating unit 194. Subsequently, the OSC is combined with a main signal by the coupler 195, and is transmitted to the long-haul WDM terminal device 20.

As described above, the alarm message
15 generated by the metro WDM terminal device 28 accommodated in the WDM-ADM device 22 is transmitted to the long-haul WDM terminal device 20 by use of the OSC-DCC for the long-haul WDM transmission. This alarm message is supplied to the message
20 processing/converting unit 88 through the long-haul WDM OSC-DCC terminal unit 80. The message processing/converting unit 88 recognizes the alarm message as a message that should be transmitted to the common EMS terminal device 34, and the metro WDM
25 terminal device 28 as an origin of the alarm message.

Additionally, the message
processing/converting unit 88 converts the format of the alarm message to a format recognizable by the common EMS terminal device 34. The alarm message
30 whose format has been converted is, then, transmitted with other messages to the common EMS terminal device 34 through the EMS interface terminal unit 84. Accordingly, alarm monitoring for a WDM terminal device, a WDM-ADM device and a SONET
35 device that compose a WDM network can be performed at one place.

The long-haul WDM terminal device 20

constantly monitors a WDM signal received from the metro WDM terminal device 28, in the network shown in FIG. 3. A description will now be given of a case in which the long-haul WDM terminal device 20 detects a change in a level (a reception level) of the received WDM signal, the change being caused by a change in a condition of an optical fiber or the like.

In the case in which the long-haul WDM terminal device 20 detects a change in the reception level, the long-haul WDM terminal device 20 notifies the metro WDM terminal device 28 about the change by using the OSC-DCC for the metro WDM transmission. The metro WDM terminal device 28 notified about the change automatically adjusts an output level of the WDM collective transmission amplifier 246 shown in FIG. 6 to be an appropriate value. Accordingly, the present invention can insure correct WDM transmission.

The WDM-ADM device 22 for the long-haul WDM transmission constantly monitors a WDM signal received from the metro WDM terminal device 28. In a case in which the WDM-ADM device 22 detects a change in a level (a reception level) of the received WDM signal, the change being caused by a change in a condition of an optical fiber or the like, the WDM-ADM device 22 notifies the metro WDM terminal device 28 accommodated in the WDM-ADM device 22 about the change by using the OSC-DCC for the metro WDM transmission. The metro WDM terminal device 28 notified about the change automatically adjusts an output level of the WDM collective transmission amplifier 246 shown in FIG. 6 to be an appropriate value. Accordingly, the present invention can insure correct WDM transmission.

According to the present invention, a wavelength-multiplexed client signal is accommodated

in or is transmitted to a next-level long-haul WDM system without being separated. Thus, the present invention achieves elimination of a WDM-DEMUX and a transponder used for separating the client signal, and a transmission transponder used for accommodating the client signal in the next-level long-haul WDM system. Consequently, the present invention achieves accommodation of the client signal at low cost.

Additionally, by transmitting a wavelength-multiplexed client signal that should be transmitted to a distant place without separating the client signal individually, the present invention achieves elimination of a WDM-DEMUX and a transponder used for separating the client signal, and a transponder and a WDM-MUX used for transmitting the client signal to the distant place. Consequently, the present invention achieves transmission of the client signal at low cost.

Further, a common EMS can collectively carry out setting and management of an entire network, by exchanging a message among an OSC-DCC for long-haul WDM transmission used by an EMS interface or in a long-haul WDM network as a data link path, an OSC-DCC for metro WDM transmission used as a data link path in a metro WDM network, and a SONET-DCC used as a data link path in a SONET network.

According to the present invention as described above, the long-haul WDM terminal device 20 or 21 can multiplex wavelengths of a plurality of client signals received from the metro WDM terminal device 28 located at a distant place, to a wavelength of another client signal without separating the plurality of client signals by each wavelength, thereby achieving accommodation of a plurality of client signals whose wavelengths are

multiplexed, at low cost.

Additionally, the long-haul WDM terminal device 20 or 21 can separate a first plurality of client signals to be transmitted to the metro WDM terminal device 28 from a second plurality of client signals without separating the first plurality of client signals by each wavelength, the wavelengths of the first plurality of client signals being multiplexed. Accordingly, the long-haul WDM terminal device 20 or 21 can accommodate the first plurality of client signals whose wavelengths are multiplexed at low cost.

The common EMS terminal device 34 can change a wavelength of each client signal transmitted by the long-haul WDM terminal device 20 or 21, the metro WDM terminal device 28, the WDM-ADM device 22, and a SONET device (the SONET-MUX 32) included in a WDM network. Thus, the WDM-ADM device 22 can add a plurality of client signals received with wavelengths of the plurality of client signals being multiplexed from the metro WDM terminal device 28 located at a distant place, to another client signal without separating the plurality of client signals by each wavelength.

Additionally, the common EMS terminal device 34 can monitor the long-haul WDM terminal device 20 or 21, the metro WDM terminal device 28, the WDM-ADM device 22, and the SONET device included in the WDM network, for an alarming condition. Further, the common EMS terminal device 34 can automatically adjust an output level of a signal from each of the long-haul WDM terminal device 20 or 21, the metro WDM terminal device 28, the WDM-ADM device 22, and the SONET device, to an appropriate value in real-time.

The WDM-ADM device 22 can add wavelengths of a plurality of client signals received from the

metro WDM terminal device 28 located at a distant place, to a wavelength of another client signal without separating the plurality of client signals by each wavelength, thereby achieving accommodation of a plurality of client signals whose wavelengths are multiplexed, at low cost.

Additionally, the WDM-ADM device 22 can drop a first plurality of client signals to be transmitted to the metro WDM terminal device 28 from a second plurality of client signals without separating the first plurality of client signals by each wavelength, the wavelengths of the first plurality of client signals being multiplexed, thereby achieving accommodation of the first plurality of client signals whose wavelengths are multiplexed at low cost.

The above description is provided in order to enable any person skilled in the art to make and use the invention and sets forth the best mode contemplated by the inventors of carrying out the invention.

The present invention is not limited to the specially disclosed embodiments and variations, and modifications may be made without departing from the scope and spirit of the invention.

The present application is based on Japanese Priority Application No. 2001-088565, filed on March 26, 2001, the entire contents of which are hereby incorporated by reference.